

New Tecpro Power Supplies



27-751 - TECPRO PS751 Power supply, single circuit

27-752 - TECPRO PB752 Power booster, dual circuit

27-753 - TECPRO PS753 Power supply, triple circuit

Dimensions: 43 x 106 x 215

27-754 - TECPRO PS754 1U power supply/booster, dual circuit

- | | |
|--------------|---|
| PS751 | 4 Male XLR's paralleled together on one Tecpro circuit. |
| PS752 | 2 Circuits with XLR input and output connectors, no audio termination. To expand existing system. |
| PS753 | 3 circuit output. Each circuit/output can be linked together. Much like the older PS711. |
| PS754 | 1U Rackmount, 2 Channel PSU/Power booster 2 Male XLR, 2 Female XLR (1 input & output connector per circuit) |

Stock code	27-711	27-751	27-752	27-753	27-754
	PS711	PS751 Free-standing system PSU, 1 channel	PB752 Free-standing power booster, 2 channel	PS753 Free-standing system PSU, 3 channel	PS754 Rackmount system PSU, 2 channel PSU/power boost
Notes			Power boost for larger systems, no audio circuit termination		
Case	Free-standing	Eurocard	Eurocard	Eurocard	1U rackmount
Front panel	Flat	Flat	Flat	Flat	Curved
No of ccts	3	4 (wired parallel, all one circuit)	2 (loop-through)	3 (separate circuits)	2
Link switches	Yes	No	No	Yes - 2 (A-B and B-C)	Yes 1 (A-B)
Link indicator	Magic eye	n/a	n/a	2 LEDs on XLR end	LED
Power output	+24V with current limit	+24V with current limit	+24V with current limit	+24V with current limit	+24V with 2 current limits
Maximum current	0.65A	2A	2A	2A	2A
Overload LED	Yes	on 4xXLR end	Yes	On 3xXLR end	Yes - two - A and B
Output connector type	XLR 3 pin male	4 x XLR 3 pin male	2 x 1 x XLR 3 pin male	3 x XLR 3 pin male	2 x XLR 3 pin male - 1 per circuit
Input connector type	n/a	n/a	2 x 1 x XLR 3 female	n/a	2 x XLR 3 pin female - 1 per circuit
PS / PB switch	n/a	n/a	n/a	n/a	On rear - switches termination on/off on both channels
					i.e. switches both channel outputs between power supply and power boost
Power LED		on 4xXLR end	On 2xXLR end	On 3xXLR end	Yes